

MIL-PRF-55339 (M55339) 射頻轉接頭

MIL-PRF-55339 (M55339) 射頻轉接頭是射頻的連接器與連接器之間的轉換，類型或延伸使用可由相同或不同的系列，及不同的插頭和插座配合轉接使用。

BNC和N有配置直角型、隔板型、三通型、直型插座和插頭。所有M55339產品均使用符合軍用規格標準，絕緣性、耐久性、RF洩漏損失和非磁性的滲透率要求的材料製作。

MIL-PRF-55339轉接頭是高頻傳輸使用，任何航天、國防或工商業環境必不可少的。佳昭公司可供應高性能M55339轉接頭，以滿足您的需求。

注意：MIL-A-55339已被MIL-PRF-55339替代。

MIL-PRF-55339產品規格

PIN Diagram

M55339	/03	- 7	XXXX
Military specification	Slant number (Table 1)	Body material & finish (Table2)	Applicable former 'UG' number or nonsignificant number

Table 1: Slant Number

Slant	Description
M55339/01	Between Series Adapter, BNC Female to Type N Female,
M55339/02	In Series Adapter, SMA Male to SMA Female, R/A
M55339/03	In Series Adapter, Type N Male to Type N Female, R/A
M55339/04	In Series Bulkhead Adapter, Type N Female to Type N Female
M55339/05	In Series Adapter, Type N Male to Type N Male
M55339/06	In Series Tee Adapter, Type N Female to Type N Female to Type N
M55339/07	In Series Adapter, Type N Female to Type N Female
M55339/08	In Series Adapter, BNC Male to BNC Female, R/A
M55339/10	In Series Bulkhead Adapter, BNC Female to BNC Female
M55339/12	In Series Adapter, BNC Male to BNC Female, R/A
M55339/13	In Series Adapter, BNC Male to BNC Male
M55339/14	Between Series Adapter, BNC Female to BNC Female
M55339/15	Between Series Tee Adapter, BNC Female to BNC Female to BNC Female
M55339/16	Between Series Adapter, BNC Male to Type N Male
M55339/17	Between Series Adapter, BNC Female to Type N Male
M55339/18	Between Series Adapter, BNC Male to Type N Female
M55339/19	In Series Adapter, BNC Male to BNC Female
M55339/20	Between Series Adapter, BNC Male to Type N Female
M55339/21	Between Series Adapter, BNC Female to Type N Female
M55339/22	In Series Bulkhead Adapter, SMA Female to SMA Female
M55339/23	In Series Adapter, SMA Male to SMA Male



佳昭企業有限公司
NEARSON ENTERPRISE CORP.

• TEL:886-2-2957-9823 • FAX:886-2-2957-9712
• <http://www.nearson.com.tw>

M55339/24	In Series Tee Adapter, SMA Female to SMA Female to SMA
M55339/25	In Series Adapter, SMA Female to SMA Female
M55339/28	In Series Adapter, TNC Male to TNC Female, R/A
M55339/29	In Series Adapter, TNC Female to TNC Female
M55339/30	In Series Bulkhead Adapter, TNC Female to TNC Female
M55339/31	In Series Tee Adapter, TNC Female to TNC Female to TNC
M55339/32	In Series Adapter, TNC Male to TNC Male
M55339/33	Between Series Adapter, TNC Female to BNC Female
M55339/34	Between Series Adapter, TNC Female to BNC Male
M55339/35	Between Series Adapter, TNC Male to BNC Male
M55339/36	Between Series Adapter, SMA Male to PTNC Female
M55339/37	Between Series Adapter, SMA Female to PTNC Female
M55339/38	Between Series Adapter, SMA Female to BNC Male
M55339/39	Between Series Adapter, SMA Male to BNC Male
M55339/40	Between Series Adapter, SMA Female to BNC Female
M55339/41	Between Series Adapter, SMA Male to BNC Female
M55339/44	Between Series Adapter, BNC Male to Type N Female
M55339/45	In Series Tee Adapter, TNC Female to TNC Female to TNC Female
M55339/46	Between Series Adapter, TNC Female to Type N Male
M55339/47	In Series Adapter, SMA Male to SMA Male, R/A
M55339/49	Between Series Adapter, BNC Female to Type N Female,
M55339/50	In Series Adapter, SMA Male to SMA Female, R/A
M55339/51	In Series Adapter, Type N Male to Type N Female, R/A
M55339/53	In Series Bulkhead Adapter, Type N Female to Type N Female

Table 2: Body Material & Finish

Designator	Description
0	Silver-plated brass
3	Passivated corrosion resistant steel
4	Gold-plated copper beryllium
6	Used between series SMA (corrosion resistant steel) and other series (brass)
7	Nickel-plated brass

若有需求或找不到產品，請佳昭公司。



佳昭企業有限公司
NEARSON ENTERPRISE CORP.

• TEL:886-2-2957-9823 • FAX:886-2-2957-9712
• <http://www.nearson.com.tw>